

R175 Rack PDU Sensor for Panduit EL2P Rack PDU

Designed for integration with Panduit's EL2P Rack PDU R175 sensor enables "wire-free" power monitoring over the RF Code radio frequency infrastructure.



Reduced cost of ownership—cost of IP address is eliminated



Real-time monitoring of PDU power metrics, alerts, alarms and warnings



One-way flow of data for enhanced security



Per phase status & metrics, including:

- Phase voltage
- Phase amperage
- Phase power
- Phase energy use



Plug and play into one of the ethernet ports on the PDU for "wire-free" power monitoring



Compatible with Panduit EL2P rack PDUs



Integrates with RF Code's CenterScape platform

RF Code's R175 power sensor offers wireless communication for use in data centers, equipment room racks and cabinets that provides continuous, automated monitoring of each rack PDU.

Power metrics and PDU information are transmitted utilizing RF Code's "wire-free" radio frequency infrastructure via the RPDU sensor. This results in a comprehensive power monitoring solution made available in RF Code's CenterScape platform.

The R175 RPDU sensor plugs into one of the Ethernet ports of the PDU and identifies the model and capabilities then relays that information to CenterScape. The R175 RPDU sensor monitors each PDU independently. This solution enables customers to monitor power metrics from each PDU at a dramatically reduced cost of ownership by reducing wires/cables, IP address allocation and network administration.

Designed for use with rack-mounted PDUs, the R175 RPDU sensor features a simple plug-and-play 433 MHz RF transmitter for quick and easy installation. Simply plug the sensor's locking RJ45 connector into one of two Ethernet ports on the PDU and attach the sensor to the top of the rack (this

ensures clear signal transmission in metal-dense data center environments).

Each sensor broadcasts its unique ID and a portion of the PDU data every 10-seconds using RF Code's patented communication protocol. All power data collected from the PDU flows via the RF Code readers to the RF Code CenterScape platform.

The software presents all the collected power parameters and computes additional attributes from this data to provide a complete picture of power utilization, power efficiency and power status.

The R175 is DC powered via an AC/DC adapter or USB power from the PDU. An internal battery supports alerts if DC power is lost, and beacons periodically to maintain connectivity with CenterScape. The R175 will continue to beacon for over 4 years using battery backup. A low battery alert is provided to indicate when the battery needs to be replaced.

In operational mode the R175 RPDU sensors only receive information from the PDUs. No outlet control or other actions are possible through the sensor.



R175 RPDU

Sensor Specifications

General Information

PDU model number
PDU serial number
PDU firmware revision
PDU message loss
PDU input phase

Alarm Information

Unit disconnect status
Unit communication status
Phase voltage and current alarms
High in-feed load (80% or more of capacity) alarm
Outlet power alarms
Sensor low-battery notification
Over current protection –
breaker-tripped alarm

Regulatory

FCC Compliance FCC Title 47 CFR Part 15; FCC ID: P6FX
CE Compliance
RED 2014/53/EU Article 3.1(a): Health and Safety
RED 2014/53/EU Article 3.1(b): Electromagnetic
Compatibility
RED 2014/53/EU Article 3.2: Radio Spectrum
CE Marked
WEEE Compliant

System Requirements

RF Code CenterScape version 1.12 and above

Power Information

Per phase voltage (V)
Per phase current flow (A)
Per phase active power (W)
Per phase apparent power (V-A)
Per phase active energy (W-hours)
Per phase apparent energy (VA-Hours)
Per phase current load balance
Per phase power factor
Per outlet average root mean square (RMS) current (A)
Per outlet apparent energy (VA-Hours) *
Per outlet active energy (W-hours) *
Per line current flow (A)

Computed Attributes in CenterScape

Per branch voltage (V)*
Per branch current flow (A) *
Per branch active power (W)*
Per branch apparent power (V-A) *
Per branch energy (kVA-Hours) *
Per outlet power factor*
Power allowance
Available current capacity per phase
Total PDU active and apparent power
Rack power redundancy